

microKORG

MIDI Commander Template Guide



FOR ABLETON MOVE

Korg microKORG – full CC control for filter, oscillators, envelopes, LFOs, mod matrix, and effects. 40 real-time CCs across 5 pages.

Default MIDI channel: 1.

Device parameters at load

Param	Value
root_note	C
scale	chromatic
layout	fourths
pad_mode	chromatic
drum_base	36
pad_color	green
velocity_curve	fixed

Pages overview

Page	Label	Channel
1	Oscillator	1
2	Filter	1
3	Amp / FX	1
4	LFO / Mod	1
5	Perform	1

Page details

Page 1 — Oscillator

Channel 1.

Encoder	Label	Full Name	Output	Notes
1	1Wv	OSC1Wav	CC 77	default 0
2	Shp	Shape	CC 14	default 0
3	Sh2	Shape2	CC 15	default 0
4	1Lv	OSC1Lvl	CC 20	default 127
5	2Wv	OSC2Wav	CC 78	default 0
6	2Md	OSC2Mod	CC 82	default 0
7	Sem	OSC2Sem	CC 18	default 64
8	2Lv	OSC2Lvl	CC 21	default 127

Page 2 — Filter

Channel 1.

Encoder	Label	Full Name	Output	Notes
1	Cut	Cutoff	CC 74	default 127
2	Res	Reso	CC 71	default 0
3	EGl	EG Int	CC 79	default 64
4	Typ	Flt Type	CC 83	default 0
5	FAk	FEG Atk	CC 23	default 0
6	FDc	FEG Dec	CC 24	default 64
7	FSu	FEG Sus	CC 25	default 64
8	FRI	FEG Rel	CC 26	default 64

Page 3 — Amp / FX

Channel 1.

Encoder	Label	Full Name	Output	Notes
1	AAk	Amp Atk	CC 73	default 0

Encoder	Label	Full Name	Output	Notes
2	ADc	Amp Dec	CC 75	default 64
3	ASu	Amp Sus	CC 70	default 127
4	ARl	Amp Rel	CC 72	default 64
5	MFS	MFX Spd	CC 12	default 64
6	MFD	MFX Dep	CC 93	default 0
7	DTm	Dly Tim	CC 13	default 64
8	DDp	Dly Dep	CC 94	default 0

Page 4 – LFO / Mod

Channel 1.

Encoder	Label	Full Name	Output	Notes
1	L1W	LFO1Wav	CC 87	default 0
2	L1F	LFO1Frq	CC 27	default 64
3	L2W	LFO2Wav	CC 88	default 0
4	L2F	LFO2Frq	CC 76	default 64
5	M1I	Mod1 I	CC 28	default 64
6	M2I	Mod2 I	CC 29	default 64
7	M3I	Mod3 I	CC 30	default 64
8	M4I	Mod4 I	CC 31	default 64

Page 5 – Perform

Channel 1.

Encoder	Label	Full Name	Output	Notes
1	Prt	Porta	CC 5	default 0
2	Vol	Volume	CC 7	default 127
3	Pan	Pan	CC 10	default 64
4	Dst	Distor	CC 92	default 0
5	Nse	Noise	CC 22	default 0
6	O2T	OSC2Tun	CC 19	default 64
7	KBT	KbdTrk	CC 85	default 64

Encoder	Label	Full Name	Output	Notes
8	Prg	Program	Program Change	

Generated from `presets/library/microkorg.json`. Regenerate via `python3 tools/generate_template_docs.py`.